




USB2.0设备共享切换器



型号： US-201

US-401

使用说明书

公司名称：北京市瑞泽胜为科技有限公司
公司地址：北京市海淀区海淀路52号北大太平洋大厦五楼506室
客服电话：400-690-8010 邮编：100080
网 址：www.shengwei.cc
工厂地址：广东省深圳市宝安区龙华镇民治村
白石龙第二工业区1栋


Company: Beijing Ruizhengwei Technology CO., Ltd
Address: NO. 506, 5th Floor, North Pacific Building, NO. 52 Haidian Road, Haidian District Beijing, China.
Tel: +86-10-82486974 Post Code: 100080
http://www.shengwei.cc
Factory Address: NO. 1 Building, Baishilong Second Industry District, Minzhi Village, Longhua, Bao'an, Shenzhen, Guangdong, China.

感谢您购买胜为品牌的 USB2.0 设备共享切换器。现如今，许多设备中含有 USB 接口。从 PC 摄像头到扫描仪，打印机，USBHUB，和 KVM 切换器。随着 USB 技术继续在计算机周边设备市场的应用，USB2.0 共享器为中小型企业提供了完全降低成本的解决方案和为家庭用户来管理其网络布局。

这个系列是为多台电脑分享一个 USB 设备。共享的 USB 2.0 开关设计了一个用户友好的界面，使设备共享更容易。没有更多的额外复杂的驱动下载程序。只要少数的点击，您就可以开始体验USB的便利。

安装示意图 (US-201):


2 口 USB B 型接口器连接到每个 PC 和1个 USB A 型的接口附加到 USB 设备上。



PC ports	2
PC port & Device port	1 USB A Type / 2 USB B Type
Module Dimension (mm)	48×70×20mm


安装示意图 (US-401):

4 口 USB B 型接口器连接到每个 PC 和1个 USB A 型的接口附加到 USB 设备上。




软件安装

- 首先把 CD-ROM 插入 CD-ROM 设备。该语言对话框将弹出。
- 如果安装不是自动开始的，启动Windows资源管理，浏览到您的CD - ROM驱动器，双击 setup.exe 文件。




- 确认选择英语为默认语言，然后单击确定。安装设置对话框。




- 默认目录是C: \ Program Files 文件的 USB 共享。如果驱动器的盘符你想安装是从C不同，浏览器代替。点击“下一步”以确认更改。




- 当安装成功对话框。点击“完成”，关闭所有打开的窗口，然后重新启动计算机。



- 在计算机重新启动时，会出现在您的桌面快捷方式和对您的屏幕右下角的图标。




操作




电脑连接设备，预备使用设备

为了使电脑连接这个设备，简单按下 Ctrl +F11 或者单击右键



这个设备由电脑A 激活

电脑 A已经使用 USB设备，这时不允在两台电脑之间转换




为了使电脑连接这个设备，

电脑连接设备，预备运行设备
简单按下Ctrl +F11或者单击右键

重要的是为最终用户实现备用的设备，例如，外部硬盘驱动器和打印机，将继续发出信号，并还回到您的计算机时，无论什么时候只要他们连接。在这过程中，USB 自动共享将混淆这一信号表明图标会出

现红色闪烁。如果你想要 USB 自动共享的控制力在不考虑设备的繁忙情况下。简单地按“Ctrl”+“F11 键”。 确认消息，然后弹出。只需点击“是”确认切换。




您还可以从一台计算机切换到另一应用程序，即使没有安装（Mac, Linux操作系统）当 LED 灯亮时表示该电脑与该设备已连接的迹象。请注意，通过前端面板选择按钮开关可以通过设备切换计算机。


注意：如果您有其他问题，请参阅更详细的文件。

软件删除

- 为了彻底从电脑中删除该软件应用程序，单击“开始”任务栏上，单击“程序”，然后“的 USB共享”，“反安装的 USB 共享”，文件删除对话框显示。点击“确定”进行确认。




- 点击“完成”。卸载该软件已经完成





USB2.0 Sharing Switch



Model: US-201

US-401


PRODUCT MANUAL

Getting started with USB 2.0 Sharing Switch

Thank you for choosing the Lianghongtai USB 2.0 Sharing Switch. Today, USB connections can be found in various devices. From PC cameras to scanners, printers. Hubs, and KVM switches. As USB technology continues its reign in the computer peripheral market, USB 2.0 Sharing Switches offer a completely cost-effective solution for the small business and home user to manage their network layout. The series are ideal for multiple PCs to share one USB device. The USB 2.0 Sharing Switch has designed a user-friendly interface that makes device sharing easier. No more extra complex driver download procedures are necessary. Only a few clicks and you can start to explore the USB adventures.

Installation(US-201):


2 USB B Type connectors connect to each PC and 1 USB A Type connector attaches to the USB device(s).



PC ports	2
PC port & Device port	1 USB A Type / 2 USB B Type
Module Dimension (mm)	48×70×20mm

Installation (US-401):


4 USB B Type connectors connect to each PC and 1 USB A Type connector attaches to the USB device(s).




PC ports	4
PC port & Device port	1 USB A Type / 4 USB B Type
Module Dimension (mm)	100X50X18mm

Software Installation


- First insert the CD-ROM into your CD-ROM drive. The language dialog box will pop up
- If installation does not start automatically. Start windows Explorer. Navigate to your CD-ROM drive and double-click the setup.exe file.



- Confirm the English is selected as the default language, and then click OK. The installation setting dialog box is displayed.




- The default directory is C:\Program Files\USB Sharing. If the drive letter where you would like to install is different from C, browse the drive instead. Click "Next" to confirm the change.



- When the installation successful dialog is displayed. Click "Finish", close all of the open windows, and then reboot your computer.



- After your computer is rebooted, there will be a shortcut in your desktop and a icon on the lower right corner of your screen.



Operation

①

Computer A



Green



Computer B



Yellow

Computer is connected to device:
Ready to use device
+F11

In order for computer to become ready to use the device, simply press Ctrl Or single right mouse click on the icon.

②

Computer A



Green



Computer B




Red

The device is actively being Used by computer A

Computer A has occupied USB device, not allow switching between PCs at This moment.


3

Computer A




In order for computer to become ready device, ready To use the device. Simply press Ctrl+F11 Or single right mouse click on the icon

Computer B



Computer is connected to device, ready to use device.

It is important for end users to realize that storage device such as, external hard drives, and printers, will continue to send signals back and forth to your computer when ever they are connected. While this is happening, USB auto sharing will be confused by this signal and an indication icon will appear red and blinking. If you would like to have the controlling power of USB auto sharing without device busy considerations, simply press "Ctrl"+"F11". The confirmation message will then pop up. Simply click "Yes" to confirm the switch




You still can switch from one computer to another even though the application is not installed (Mac Linux OS) When the LED light is lit

that is an indication that the PCs are connected with the device already. Please be aware that switching computers by the front panel Select button will force the device to switch with the computer.

Note: Please refer the read me file for more detail if you have other questions

Software Uninstallation

- In order to completely remove the software application from your PC, click "Start" on the task bar, click "Programs", then "USB Sharing", "Uninstall USB Sharing", The File Deletion dialog is display. Click "OK" to confirm.



- Click "Finish". The software uninstallation has been completed

